




# Control valve(3/2 way, 5/3 way)

## CM3 Series

### ■ Installation and operation

1. Mounting way: by body, by panel I, by panel II, latching type, mushroom type. Please refer to the following picture:




- The control set is made of engineering plastic which only allows manual operation and switching valves through metal impact is forbidden.
- The series of CM3B, CM3L, CM3V, CM3R, CM3PM, CM3PMS, CM3PMX, CM3PF, CM3PP get the function of automatic restoration. The hand valves of CM3Y, CM3HS, CM3HD, CM3PL are in type of manual restoration. CM3PL will be restored by turning the revolve button after being pressed into orientation.
- Pay attention to the reversing stroke. The reversing stroke can not surpass its stroke stipulated in stroke control table when the direction-change of the valve is forced by any external forces, otherwise it will cause the damage of the valve.


Type	Spool stroke	Button (Roller/Handle) stroke	Type	Spool stroke	Button (Roller/Handle) stroke
CM3B05(06)	1.5~3.0	-	CM3B08	2.4~4.0	-
CM3R05(06)	1.5~2.5	3.0~4.8	CM3R08	2.4~3.2	6.8~9.0
CM3L05(06)	1.5~2.3	3.0~4.8	CM3L08	2.4~3.2	7.2~9.7
CM3V05(06)	1.5~3.0	2.7~4.2	CM3V08	2.4~4.0	2.6~4.2
CM3Y05(06)	1.5~2.5	3.0~4.8	CM3Y08	2.4~3.2	6.8~9.0
CM3PL05(06)	1.5~2.5	4.0~5.0	CM3PL08	2.4~3.5	4.0~5.0
CM3PP05(06)	1.5~3.0	4.0~5.5	CM3PP08	2.4~4.0	4.0~5.5
CM3PF05(06)	1.5~3.0	4.0~5.5	CM3PF08	2.4~4.0	4.0~5.5
CM3HS05(06)	1.5~3.0	4.0~5.5	CM3HS08	2.4~4.0	4.0~5.5
CM3HD05(06)	1.5~3.0	4.0~5.5	CM3HD08	2.4~4.0	4.0~5.5
CM3PM05(06)	1.5~3.0	4.0~5.5	CM3PM08	2.4~4.0	4.0~5.5
CM3PMS05(06)	1.5~3.0	4.0~5.5	CM3PMX08	2.4~4.0	4.0~5.5
CM3PMX05(06)	1.5~3.0	4.0~5.5	CM3PMX08	2.4~4.0	4.0~5.5

- The CM3L can only switch the valve in single direction (impact from left to right). The impact from the other direction (from right to left) is invalid.
- Control joint combination can be ordered individually. Please refer to external specification.

### ■ Inner structure



### ■ Dimension (Basic type)




# Control valve(3/2 way, 5/3 way)

## CM3 Series


### Control set dimension

#### CM3R06-P1




Note: CM3R06 control joint, which used in CM3R05 and CM3R06, can not be ordered individually. It should be matched with basic type.

#### CM3L06-P1




Note: CM3L06 control joint, which used in CM3L05 and CM3L06, can not be ordered individually. It should be matched with basic type.

#### CM3R08-P1




Ordering code	CM3R08-P1
Type	CM3R08 roller type control set
Applicable products	CM3R08

#### CM3L08-P1




Ordering code	CM3L08-P1
Type	CM3L08 roller type control set
Applicable products	CM3L08

#### CM3V06-P1




Ordering code	CM3V06-P1
Type	CM3V vertical type control set
Applicable products	CM3V05 CM3V06 CM3V08

#### CM3Y06-P1




Ordering code	CM3Y06-P1
Type	CM3Y lever type control set
Applicable products	CM3Y05 CM3Y06 CM3Y08

#### CM3PL06-P2




Ordering code	CM3PL06-P2
Type	CM3PL latching type control set(red)
Applicable products	CM3PL05 CM3PL06 CM3PL08

#### CM3PP06-P1



Ordering code	CM3PP06-P1
Type	CM3PP protruding type control set(green)
Applicable products	CM3PP05 CM3PP06 CM3PP08
Ordering code	CM3PP06-P2
Type	CM3PP protruding type control set(red)
Applicable products	CM3PP05 CM3PP06 CM3PP08
Ordering code	CM3PP06-P3
Type	CM3PP protruding type control set(black)
Applicable products	CM3PP05 CM3PP06 CM3PP08
Ordering code	CM3PP06-P4
Type	CM3PP protruding type control set(yellow)
Applicable products	CM3PP05 CM3PP06 CM3PP08

#### CM3PF06-P1



Ordering code	CM3PF06-P1
Type	CM3PF flat type control set(green)
Applicable products	CM3PF05 CM3PF06 CM3PF08
Ordering code	CM3PF06-P2
Type	CM3PF flat type control set(red)
Applicable products	CM3PF05 CM3PF06 CM3PF08
Ordering code	CM3PF06-P3
Type	CM3PF flat type control set(black)
Applicable products	CM3PF05 CM3PF06 CM3PF08
Ordering code	CM3PF06-P4
Type	CM3PF flat type control set(yellow)
Applicable products	CM3PF05 CM3PF06 CM3PF08




CM3

# Control valve(3/2 way, 5/3 way)

## CM3 Series




### CM3PM06-P




Ordering code	CM3PM06-P1
Type	CM3PM mushroom type control set(green)
Applicable products	CM3PM05 CM3PM06 CM3PM08
Ordering code	CM3PM06-P2
Type	CM3PM mushroom type control set(red)
Applicable products	CM3PM05 CM3PM06 CM3PM08
Ordering code	CM3PM06-P3
Type	CM3PM mushroom type control set(black)
Applicable products	CM3PM05 CM3PM06 CM3PM08
Ordering code	CM3PM06-P4
Type	CM3PM mushroom type control set(yellow)
Applicable products	CM3PM05 CM3PM06 CM3PM08

### CM3HS06-P




Ordering code	CM3HS06-P1
Type	CM3HS selector type control set(green)
Applicable products	CM3HS05 CM3HS06 CM3HS08
Ordering code	CM3HS06-P2
Type	CM3HS selector type control set(red)
Applicable products	CM3HS05 CM3HS06 CM3HS08
Ordering code	CM3HS06-P3
Type	CM3HS selector type control set(black)
Applicable products	CM3HS05 CM3HS06 CM3HS08
Ordering code	CM3HS06-P4
Type	CM3HS selector type control set(yellow)
Applicable products	CM3HS05 CM3HS06 CM3HS08

### CM3PMX06-P







Ordering code	CM3PMX06-P1
Type	CM3PMX big mushroom type control set(green with guard)
Applicable products	CM3PMX05 CM3PMX06 CM3PMX08
Ordering code	CM3PMX06-P2
Type	CM3PMX big mushroom type control set(red with guard)
Applicable products	CM3PMX05 CM3PMX06 CM3PMX08
Ordering code	CM3PMX06-P3
Type	CM3PMX big mushroom type control set(black with guard)
Applicable products	CM3PMX05 CM3PMX06 CM3PMX08
Ordering code	CM3PMX06-P4
Type	CM3PMX big mushroom type control set(yellow with guard)
Applicable products	CM3PMX05 CM3PMX06 CM3PMX08

### CM3PMS06-P



Ordering code	CM3PMS06-P1
Type	CM3PMS mushroom type control set(green with guard)
Applicable products	CM3PMS05 CM3PMS06 CM3PMS08
Ordering code	CM3PMS06-P2
Type	CM3PMS mushroom type control set(red with guard)
Applicable products	CM3PMS05 CM3PMS06 CM3PMS08
Ordering code	CM3PMS06-P3
Type	CM3PMS mushroom type control set(black with guard)
Applicable products	CM3PMS05 CM3PMS06 CM3PMS08
Ordering code	CM3PMS06-P4
Type	CM3PMS mushroom type control set(yellow with guard)
Applicable products	CM3PMS05 CM3PMS06 CM3PMS08

### CM3HD06-P



Ordering code	CM3HD06-P1
Type	CM3HD double-selector type control set(green)
Applicable products	CM3HD05 CM3HD06 CM3HD08
Ordering code	CM3HD06-P2
Type	CM3HD double-selector type control set(red)
Applicable products	CM3HD05 CM3HD06 CM3HD08
Ordering code	CM3HD06-P3
Type	CM3HD double-selector type control set(black)
Applicable products	CM3HD05 CM3HD06 CM3HD08
Ordering code	CM3HD06-P4
Type	CM3HD double-selector type control set(yellow)
Applicable products	CM3HD05 CM3HD06 CM3HD08

Note: CM3HD control joint can be ordered individually, but should be matched with the body of CM3HD.

